EXTRACT THE TOOL & SOFTWARE FROM RAR TO FOLDER

NOTE : Software Upgrade tool for Windows XP and Windows 8

Step 01 : Download the WIN RAR file from website

Can download from this link also - <u>http://www.filehippo.com/search?q=rar</u>

Note :- If you already have WIN RAR software, then no need to download again

Step 02: Right click on RAR file (sent by we transfer) & choose to Extract the files..



EXTRACT THE TOOL & SOFTWARE FROM RAR TO FOLDER

Step 03 : Inside the folder have a file as below , pl. extract this also



Step 04 : Extract the software from RAR file

ZURI_S56_A_Ver_08_2016-6-3





Step 05 : Open the Following folder

"S56_Tool" → "SA" → "Driver_Auto_Installer_EXE_v5.1453.03" Go in WIN_8 or WIN7_WINXP folder (according to your PC configuration) & Install the driver.
DriverInstall

Step 06 : Open the Following folder

"S56_Tool"

- → "S56_Tool "
- → "Driver_Auto_Installer_EXE_v1.1236.00"
- → "Driver_Auto_Installer_EXE_v1.1236.00"
- \rightarrow "SmartPhoneDriver "
- →Driver_Auto_Installer_v1.1236.00"
- \rightarrow Go in X64 or X86 folder (according to your PC configuration)

→Install the driv 🗐 spinstall

→Install the drive _{dpinst}

Step 07: Open the Following folder

- "S56_Tool"
- → "S56_Tool "
- →" SP_Flash_Tool_exe_Windows_v5.1516.00"
- → "SP_Flash_Tool_exe_Windows_v5.1516.00" and Find "flash_tool"



INSTALL THE -- > PHONE DRIVER IN YOUR PC

Step 08 : Make the phone "Factory Reset" & Make it ON

Step 09 : Connect the Phone with your PC through USB cable

Check Point :- Make sure USB cable shall be of Phone (Not Power Bank)

Driver Software Installation		×
Your device is ready to use		
USB Mass Storage Device Linux File-CD Gadget USB Device Linux File-CD Gadget USB Device	Ready to use Ready to use Ready to use	
		Close

PC will take the Phone Driver Automatically & after successful install ... message as above picture shall appear

<u>Note</u>

If you already connected this phone before with same PC then it will not show the Driver update process & the above message will not appear

Means -- > Your PC already have the Phone Driver

UPLOAD THE -- > New Software in Phone

Step 10 : Open the folder "SP_Flash_Tool_exe_Windows_v5.1516.00" and Find "flash_tool"

📓 Smart Phone Flash Too	ol(Runtime Trace Mode)	$ \Box$ \times
File Options Window	Help	
	Welcome Format Download Readback Memory Test	
вм	Download Stop	
	Download-Agent	Download Agent
MediaTek	Scatter-loading File	Scatter-loading
	Name Begin Address End Address Location	
		This window Will open
	0% 0 B/s 0 Bytes High Speed 0:00	

Step 11 : Select the software to be Upload

Click here & Navigate to the folder where the file "ZURI_S56_A_Ver_08_2016-6-3" was Extracted And open folder "IMAGE" and Select the file "MT6592_Android_scatter"

Smart Phone Flash Tool(Runtime Trace Mode) - D X	
File Options Window Help	
Welcome Format Download Readback Memory Test Download Stop Download Stop Download-Agent _Tool_exe_Windows_v5.1516.00\MTK_AllInOne_DA.bin Download Agent Scatter-loading File	
Firmware Upgrade dress End Address Location	
0% 0 B/s 0 Bytes High Speed 0:00	

After select the software -- > It will upload in Tool & Status will show here -- > Wait until complete

UPLOAD THE -- > New Software in Phone

Step 12 : Make the Phone "OFF" -- > Remove the Battery -- > Again Insert the Battery

Check Point :- Only Insert the Battery, But do not make the Phone "ON"

Step 12 : Click Download -- > Press the Vol -ve key of Phone -- > Connect the USB to Phone

🗧 Smart Phone Flash To	ol(Runtime Trace Mode				_		\times
File Options Window	Help						
	Welcome Format	Download	Readback	Memory Test			
вм	Download St	ор					
	Download-Agent	1_Tool_exe_Win	dows_v5.1516.	00\MTK_AllInOne	e_DA.bin 🗎 Dov	vnload Age	ent
MediaTek	Scatter-loading File				🗾 🔚 Sca	tter-loadin	g

After Connect the USB to Phone -- > Software upload to phone will Start -- > & Will Show the Below Progress



After Complete the successful loading of Software -- > Will Show the Download OK



Note: Sometimes this Process does not complete at first attempt. If it Fails , Try few more times

Step 13 : If Software not upload successfully -- > Will Show Fail

Pl. Note :- If getting fail -- > Pl. try again from **Step 11**

Step 14 : Remove the battery -- > Insert it again and turn the Phone ON.

Pl. Note :- First Boot after new software installation will take time probably about 10minutes.